




N-Adapter to PDR84, female  
gasket and screw kit enclosure

#### FEATURES / BENEFITS

Waveguide installation

- The rectangular waveguide component provides simple installation in particular difficult cases
- The flange adapter provides proper matching of rectangular waveguide flanges to N-female connector
- It provides outstanding electrical performance



## Technical features

### STRUCTURE

Type of Rectangular Waveguide Component		Waveguide to Type N Female Coax Adapter
Waveguide Size IEC (EIA)		R84 (WR112)
Coaxial Interface		N-female
Flange		PDR84
Flange Finish		Brass un-plated

### ELECTRICAL SPECIFICATIONS

Frequency Range	GHz	6.57 - 9.99
Minimum Return Loss (max. VSWR)	dB (VSWR)	26.4 (1.10)

### MATERIAL

Material		Brass
Color		Black

### PACKAGING INFORMATION

Package Quantity		1
------------------	--	---

[External Document Links](#)

[Notes](#)